Т

Α

S

Η

Ε

E

Т

Model: 71T

THE DEEP END

As far as our pool analogies go, the Deep-end perfectly highlights the qualities of this pot. If you have long leads that you need to tin, you aren't going to find a better solder pot on the market for the money. It takes approximately 8 bars of our CS-PBF4 to fill 'the Deep End' Solder pot.



FEATURES AND BENEFITS

Includes removable dross tray and attached sand tray.

1000 watts of thermostatically controlled power

TECHNICAL SPECIFICATIONS

| RoHS Compliant | Yes |
|--------------------------------|-----------------------|
| Wattage | 1000 watts |
| Maximum Temperature | 900 °F / 482°C |
| Solder Bath Depth | 4.25 in / 10.80 cm |
| Solder Bath Diameter | 3-1/8 in |
| Country of Origin | US |
| Net Volume | Approx. 18 oz |
| Package Dimensions (Inches) | 12 x 12 x 12 |
| Package Weight | 15 lbs / 6.80 kg |

REPLACEMENT PARTS

The following products can be used as replacements for Model 71T featured on this page:

| Model | Product Name |
|----------|--------------------------------|
| PE710020 | Replacement Solder Pot Element |
| PT1280 | Replacement Thermostat |