

# Model: 71T

## THE DEEP END

As far as our pool analogies go, the Deep-end perfectly highlights the qualities of this pot. If you have long leads that you need to tin, you aren't going to find a better solder pot on the market for the money. It takes approximately 8 bars of our CS-PBF4 to fill 'the Deep End' Solder pot.



### TECHNICAL SPECIFICATIONS

|                             |                    |
|-----------------------------|--------------------|
| RoHS Compliant              | Yes                |
| Wattage                     | 1000 watts         |
| Maximum Temperature         | 900 °F / 482°C     |
| Solder Bath Depth           | 4.25 in / 10.80 cm |
| Solder Bath Diameter        | 3-1/8 in           |
| Country of Origin           | US                 |
| Net Volume                  | Approx. 18 oz      |
| Package Dimensions (Inches) | 12 x 12 x 12       |
| Package Weight              | 15 lbs / 6.80 kg   |

### FEATURES AND BENEFITS

- Includes removable dross tray and attached sand tray.
- 1000 watts of thermostatically controlled power

### REPLACEMENT PARTS

The following products can be used as replacements for Model 71T featured on this page:

| Model    | Product Name                   |
|----------|--------------------------------|
| PE710020 | Replacement Solder Pot Element |
| PT1280   | Replacement Thermostat         |